

## OMNITRONIC PM-404 DJ Mixer

PRO 2-channel DJ mixer

Art.n.: 10006817

GTIN: 4026397313444



**L'articolo non è più disponibile.**

### Descrizione :

What is your demand?

It does not always necessarily need to be the biggest, the most expensive and most beautiful, does it? A thinking that is true of many fields. Our OMNITRONIC PM-404 DJ mixer sets an appropriate example. Because like cars, cameras or televisions, DJ-mixers do as well offer bigger and smaller versions. The own demand is the decisive factor. You need a reliable, solid standard mixer with current standard features and an appealing design? For you two input channels with gain control and a 3-way equalizer, one microphone channel with a 2-way equalizer and talkover function, a replaceable crossfader, super-smooth channel faders, a 10-digit stereo LED level meter and master level control, two switchable line/phono inputs and a headphone input of course are enough? Then the PM-404 is your choice. Because this mixer is an uncomplicated and unexpensive alternative for the home mixing area as well as for a bar with DJ. Sometimes it doesn't need more to be satisfied!

### Features :

- 2 input channels with gain control and 3-way equalizer with kill function
- Level control, 2-way equalizer and talkover button for the DJ microphone channel
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output, with cue mix control
- Replaceable crossfader for crossfading between input channels A and B
- High-quality and super-smooth channel faders
- 10-digit stereo LED level meter and master level control
- Inputs: 2 x line/phono (stereo RCA), switchable; DJ microphone and headphones (both 6.3 mm jack)
- Outputs: master and record (both stereo RCA)
- Operation via supplied power unit

### Logistica

EAN / GTIN: 4026397313444

Peso : 3,30 kg

Lunghezza : 0.39 m

Larghezza : 0.27 m

Altezza : 0.13 m

## Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza totale installata:	5,00 W
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite connettore cavo (M) versione da incasso cavo di alimentazione con alimentatore a spina (in dotazione)
Intervallo di frequenza:	20 - 20000 Hz
Misure:	Larghezza: 25,5 cm Profondità: 26,2 cm Altezza: 8,4 cm
Peso:	2,8 kg via supplied power unit
Inputs:	
DJ microphone:	6.3 mm jack
Minimum input voltage:	1.5 mV RMS/ 1 kohms
LINE 1-2:	stereo RCA
Minimum input voltage:	150 mV RMS/ 270 kohms
PHONO 1-2:	stereo RCA
Minimum input voltage:	3 mV RMS/ 470 kohms
Outputs:	
MASTER:	stereo RCA
Max. output level:	+22 dBu
Output voltage:	9 V RMS
REC:	stereo RCA
Output voltage:	225 mV RMS/ 5 kohms
Headphones output:	6.3 mm stereo jack/ 16 ohms
Tone control:	
2 x High:	-26 dB to +12 dB/ 12 kHz
2 x Middle:	±15 dB/ 2.5 kHz
2 x Low:	-26 dB to +12 dB/ 80 Hz
S/N ratio:	>80 dB
Distortion:	<0.02% (line/phono)